

# Pure Sine Wave DC to AC Power Inverter - P Series

## Inverter Expert **P600-600W with USB**

### Features: ■

Input & output fully isolated. ◀

With USB output port ◀

**High Surge:** High surge current capability starts difficult loads such as TVs, ◀  
camps, motors and other inductive loads.

**Soft start:** Smooth start-up of the appliances. ◀

**Pure Sine Wave Output Waveform:** Clean power for sensitive loads. ◀

**AC output** identical to, and in some cases ◀

better than the power supplied by your utility.

**Cooling Fan:** Control by load or temperature (optional) ◀

**Low Total Harmonic Distortion:** below 3% ◀

### AC Output Receptacles(optional)

A	B	C	D	E	F	G	H	I	GFCI
USA	AUSTRALIA	UNIVERSAL	Europe+USA+Japan	U.K	FRANCE	GERMANY	BRAZIL	ISRAEL	USA-GFCI





RoHS



2 YEAR LIMITED WARRANTY

### ■ SPECIFICATION:

MODEL		P600-121	P600-241	P600-481	P600-122	P600-242	P600-482
OUTPUT	AC VOLTAGE	100/110/120VAC			220/230/240VAC		
	RATED POWER	600W					
	SURGE POWER	1200W(for few seconds)					
	USB	5V, 2.1A					
	WAVEFORM	Pure Sine Wave(THD<3%)					
	FREQUENCY	50/60Hz ±3Hz					
	AC REGULATION	±5%					
	STANDARD RECEPTACLES	A, B, C, D, E, F, G, H, I, GFCI(optional as above)					
LED INDICATOR		Green for power on, red for failure / protection status indication					
INPUT	NO LOAD CURRENT DRAW	≤0.7A					
	DC VOLTAGE	12V	24V	48V	12V	24V	48V
	VOLTAGE RANGE	10.5~15.0VDC	21.0-30.0V DC	42~60V DC	10.5~15.0VDC	21.0-30.0V DC	42~60V DC
	EFFICIENCY (Typ.)	>87.0%	>90.0%	>90.0%	>90.0%	>90.0%	>90.0%
	FUSE	40A*2	20A*2	10A*2	40A*2	20A*2	10A*2
	DC CABLE	BVR4*2	BVR4*2	BVR4*2	BVR4*2	BVR4*2	BVR4*2
	PROTECTION	BAT.LOW ALARM	11±0.5V DC	22±1V DC	44±2V DC	11±0.5V DC	22±1V DC
BAT.LOW SHUTDOWN		10.5±0.5V DC	21.0±15V DC	42±2V DC	10.5±0.5V DC	21.0±1V DC	42±2V DC
OVERLOAD		Shutdown					
OVER VOLTAGE		14.8±0.5V DC	29.6±1V DC	58.4±2V DC	14.8±0.5V DC	29.6±1V DC	58.4±2V DC
OVER TEMPRETURE		Shut-off output voltage, recover automatically after temperature goes down					
SHORT CIRCUIT		Shut-off output voltage, repower on to recover					
BAT.REVERSE POLARITY		By fuse open					
SOFT START		Yes 5~10s					
EARTH LEAKAGE		Yes					
ENVIRONMENT		RESET VOLTAGE AFTER LVS	11.8~12.8V DC	23.6~25.6V DC	47.2~51.2V DC	11.8~12.8V DC	23.6~25.6V DC
	WORKING TEMP.	0-40°C					
	WORKING HUMIDITY	20%-90% RH non-condensing					
SAFETY & EMC	STORAGE TEMP.& HUMIDITY	-30°C-70°C 22° F-185° F、10-95%					
	SAFETY STANDARDS	UL458(only for GFCI receptacle)					
	ISOLATION RESISTANCE	I/P-O/P: 1000Ohms/500VDC					
	EMI CONDUCTION & RADIATION	Compliance to EN55022 Class A					
	EMS IMMUNITY	Compliance to EN61000-3-2, 3					
	LVD	Compliance to EN60950-1: 2006+A11:2009					
OTHERS	E- MARK	Compliance to E8*72/245/EEC, 95/54/EC					
	DIMENSION	260*150*77.7mm					
	PACKING	2.1Kg, 6pcs/15.6Kgs/Ctn(57*30.5*30cm)					
	COOLING FAN	Control by load/temperature(optional)					
APPLICATION		Home and office appliances, Power tools and portable equipments, Vehicle and solar power systems .....etc.					



### INSTALLATION

