

Voltage Booster SUT Series(SUT1224-20)

Convert the DC Power from 12V to 24V 20A



• Description

The product can convert 12VDC of automobile to 24VDC, and its output rated current is 20A.

Appliance in automobile whose service power is less than 480W, and the voltage is 24VDC can be used by the product.

For low-voltage apparatus whose current is less than 20A, and input volts DC is less than 16V, and output volts DC is 24V or others.

• Features

- 100% New components used
- Real power
- Cooling fan control
- Dual color LED indicate the power & failure status

• Specifications

Model	SUT1224-20
Input Voltage	12V
Output Voltage	24V
Output Current	20A
DC Input Voltage Range	10-16V DC
Rated Power	480W
Max. Power	528W
The Lowest Input Voltage	DC10V±0.5V
The Highest Output Voltage	DC32V±0.5V
The Rated Output Voltage	DC24V±10%
Working Temperature	50°C ±20%
Measurement	157*91*47mm
N.W.	0.45Kg
Packing	40pcs